



alpha **VIEW** alpha **SOUND**

alpha **LINK**



Linux operating system  
Web browser  
Preinstalled apps  
DLNA / Miracast Mirroring



**Bluetooth 4.2** - Even faster connection establishment, more range (up to 100m) and less consumption (low energy)

#### Highlight von Bluetooth 4.2:

The alphatronics TV can transmit the audio signal via Bluetooth or send the music from your mobile phone play the TV.

Model		T-19 SBI+
SCREEN	Screen size	47 cm (19")
	alphatronicsView wide-angle display (178°/178°)	LED display
	Image format	16:9 Widescreen
	Resolution	1366 x 768
	Contrast ratio	3000:1
	Brightness value	300 cd/m <sup>2</sup>
	Response time	< 5 ms
	Viewing angle	178 H, 178 V
TUNER	PAL B/G, NTSC, SECAM	•
SOUND	Music output / Watt	2 x 5 W
	Integrated speakers	•
	Stereo sound	•
CONNECTIONS	TV tuner	•
	2x HDMI connections	•
	Headphones (3.5 mm)	•
	AV in / AV out	•
	YPbPR connection (3.5 mm)	•
	Digital Coaxial Out	•
	10.8 - 26 V DC supply voltage	•
	External power supply 100 - 240 V AC, 12 DC	•
	alphatronics-Sound	•
	Pairing via OSD menu	•
TUNER	Triple tuner (DVB-S2, DVB-T2 HD, DVB-C tuner - HDTV MPEG2/4)	•
	Integrated display of the quality level (DVB-S2)	•
	CI+ slot (Common Interface)	•
	Electronic Programme Guide (EPG)	•
	Favourites list	•
	Parental control	•
PhotoViewer	USB 2.0 connection / Media player (PVR feature can be retrofitted)	•
Internet	Basic Smart feature	•
FEATURES	Automatic station search storage	•
	Max. TV programme slots	999
	Videotext TOP (100 pages)	•
	Image modes - number	4
	Sound modes - number	5
	Sleep timer	•
	Graphical OSD menu (multilingual)	•
GENERAL	Power consumption	Operation < 19 W (max.) Standby < 0.5 W
	Weight	With base 2.7 kg Without base 2.4 kg
	Dimensions (W x H x D in mm)	<div> </div> With base: 438 x 310 x 153 Without base: 438 x 275 x 43
	Housing colour	Brushed silver
Accessories	HD-ready	•
	VESA Standard (100 x 100 mm)	•
	Energy efficiency class	A
	On/off switch	•
	Remote control, AN5 DVB-T antenna, mains adapter, YPbPR adapter, AV adapter, batteries, operating instructions	•



alpha **VIEW** alpha **SOUND**

alpha **LINK**



Linux operating system  
Web browser  
Preinstalled apps  
DLNA / Miracast Mirroring



**Bluetooth 4.2** - Even faster connection establishment, more range (up to 100m) and less consumption (low energy)

#### Highlight von Bluetooth 4.2:

The alphatronics TV can transmit the audio signal via Bluetooth or send the music from your mobile phone play the TV.

Model	T-22 SBI+	
SCREEN	Screen size	55 cm (22")
	alphatronicsView wide-angle display (178°/178°)	LED display
	Image format	16:9 Widescreen
	Resolution	1920 x 1080 Full-HD
	Contrast ratio	1,000:1
	Brightness value	300 cd/m <sup>2</sup>
	Response time	< 5 ms
	Viewing angle	178 H, 178 V
TUNER	PAL B/G, NTSC, SECAM	•
SOUND	Music output / Watt	2 x 5 W
	Integrated speakers	•
	Stereo sound	•
CONNECTIONS	TV tuner	•
	2x HDMI connections	•
	Headphones (3.5 mm)	•
	AV in / AV out	•
	YPbPR connection (3.5 mm)	•
	Digital Coaxial Out	•
	10.8 - 26 V DC supply voltage	•
	External power supply 100 - 240 V AC, 12 DC	•
	alphatronics-Sound	•
	Pairing via OSD menu	•
TUNER	Triple tuner (DVB-S2, DVB-T2 HD, DVB-C tuner - HDTV MPEG2/4)	•
	Integrated display of the quality level (DVB-S2)	•
	CI+ slot (Common Interface)	•
	Electronic Programme Guide (EPG)	•
	Favourites list	•
	Parental control	•
PhotoViewer	USB 2.0 connection / Media player (PVR feature can be retrofitted)	•
Internet	Basic Smart feature	•
FEATURES	Automatic station search storage	•
	Max. TV programme slots	999
	Videotext TOP (100 pages)	•
	Image modes - number	4
	Sound modes - number	5
	Sleep timer	•
	Graphical OSD menu (multilingual)	•
GENERAL	Power consumption	Operation < 24 W (max.) Standby < 0.5 W
	Weight	With base 3.3 kg Without base 3.0 kg
	Dimensions (W x H x D in mm)	<div> </div> With base: 503 x 342 x 153 Without base: 503 x 312 x 43
	Housing colour	Brushed silver
Accessories	HD-ready	• / Full HD
	VESA Standard (100 x 100 mm)	•
	Energy efficiency class	A
	On/off switch	•
	Remote control, AN5 DVB-T antenna, mains adapter, YPbPR adapter, AV adapter, batteries, operating instructions	•